



Product operation sketch

- 1.ON State
2. Off State
3. Bluetooth State



4. Audio Jack
5. Indicator
6. Charging Socket



Operational Approach

I. Turn ON

1. Slide the button to the "ON" position on the bottom of the speaker, and red indicator will light. It can play audio signal when plug the audio cable in this state.
2. Slide the button to the "Bluetooth" position on the bottom of the speaker, LED indicator will flash blue and startup music to enter the pairing mode.
3. Slide the button to the center position on the bottom of the speaker to turn off.
4. Bluetooth pairing and connection:
The Bluetooth device will show the pairing name "X-HORN" after Bluetooth device search the speaker ; Select the pairing name from the list of discovered devices on your Bluetooth device list and confirm, then the speaker will pairing automatically.(If prompted for a password, enter "0000" (4 zeros).If the connection is successful, two audible beeps will sound on your device, the Bluetooth LED indicator will remain blue, it can play Bluetooth signal.

Operational Approach

II. Charging

1. Please charge when you heard the alarm "beep "during playing the music.
2. Insert the USB charge wire this speaker comes with into the 3.0 charge port in the turn off state, the other end switch on the computer USB port or 5V charger. Switch on the power can be charged for the speaker, the power is saturated when the red light off, and you can cut off the power source.it can play Bluetooth signal.

Note

1. The red light will brighter when charge in the play the audio signal
2. Red alternates flash with Blue light when charge in the playing Bluetooth state.
3. Red indicator will light when charge in the turn off state.
4. Please keep the products in the turn off state if don't work.
5. If the products don't work (more than 3 months) for a long time, please charge on it.

Operational Approach

III. Technical specifications

Bluetooth Specification	2.1 + EDR
Bluetooth protocol	A2DP AVRCP
RF Range	10 M
Frequency Response	100HZ-20KHZ
Signal-To-Noise	≥85db
Distortion	≤0.1 %
Working voltage / current	3.3 ~ 4.5V
Charging voltage / current	USB 5V
Net Weight	122g
Gross Weigh	220g
Product dimension	94 x 59.5mm
Packaging	111 x 70 x 141mm
Playback Time	4H
Charging Time	2H
Battery Capacity	400mA
Loudspeaker Output	4Ω x 3W x 1

Operational Approach

IV. Package Contents



1. X-HORN BT speaker



2. Audio cable



3. USB charge cable



4. User Manual



5. Bike Mount

Operational Approach

V. Bike Mount

